PANEL: A
LOCATION: BLDG UNIT 1A – BEDROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 2 TON	30	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 5 KW	30	2	2500			1000	1	20	MICROWAVE / VENTHOOD	ø12	6
7					2500			1680	1	20	REFRIGERATOR, DESK RECEPTACLE	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			1500	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	BEDROOM & SMOKE DETECTORS	*20	1	1120			640	1	20	RECEPTACLES – DINING	ø12	14
15	ø12	LIGHTS & EXHAUST – BA3H	20	1	150			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS – UTILITY, KITCH, DINING, ENTRY, LIVING, STOR., PATIO	20	1	600			1440	1	20	RECEPTACLES – LIVING, PATIO, HALL, ENTRY	ø12	18
19	ø0	DRYER	30	2	3500			160	1	20	RECEPTACLE – BA3H	ø12	20
21					3500			1080	1	20	RECEPTACLES – UTILITY, WASHER	ø12	22
23	–	SPARE	20	1	–			–	1	20	SPARE	–	24

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,050
A=23,175 B=21,875

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: B
LOCATION: BLDG UNIT 1B – UTILITY ROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 2 TON	30	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 5 KW	30	2	2500			1000	1	20	MICROWAVE / VENTHOOD	ø12	6
7					2500			1680	1	20	REFRIGERATOR, DESK RECEPTACLE	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			640	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	BEDROOM & SMOKE DETECTORS	*20	1	1120			1600	1	20	RECEPTICALS – DINING	ø12	14
15	ø12	LIGHTS & EXHAUST – BA3H	20	1	150			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS – UTILITY, KITCH, DINING, ENTRY, LIVING, STOR., PATIO	20	1	600			1440	1	20	RECEPTACLES – LIVING, PATIO, HALL, ENTRY	ø12	18
19	ø0	DRYER	30	2	3500			160	1	20	RECEPTACLES – BA3H	ø12	20
21					3500			1080	1	20	RECEPTACLES – UTILITY, WASHER	ø12	22
23	–	SPARE	20	1	–			–	1	20	SPARE	–	24

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,050
A=23,175 B=21,875

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: C
LOCATION: BLDG UNIT 1A–HC – BEDROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 2 TON	30	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 5 KW	30	2	2500			100	1	20	VENTHOOD	ø12	6
7					2500			1480	1	20	REFRIGERATOR	ø12	8
9	ø0	WATER HEATER	30	2	3600			1000	1	20	MICROWAVE	ø12	10
11					3600			1500	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	BEDROOM, SMOKE DETECTORS	*20	1	1120			640	1	20	RECEPTACLES – DINING	ø12	14
15	ø12	LIGHTS & EXHAUST – BA3H	20	1	150			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS – UTILITY, KITCH,DINING ENTRY, LIVING, STOR., PATIO	20	1	600			1600	1	20	RECEPTACLES – COUNTER	ø12	18
19	ø0	DRYER	30	2	3500			160	1	20	RECEPTACLES – BA3H	ø12	20
21					3500			1080	1	20	RECEPTACLES – UTILITY, WASHER	ø12	22
23	–	SPARE	20	1	–			–	1	20	SPARE	ø12	24

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,450
A=21,625 B=23,825

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: D
LOCATION: BLDG UNIT 2A – BEDROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 2.5 TON	40	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 7.5 KW	40	2	2750			1000	1	20	MICROWAVE / VENTHOOD	ø12	6
7					2750			1480	1	20	REFRIGERATOR	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			1000	1	20	GARBAGE DISPOSAL, DISH WASHER	ø12	12
13	ø12	BEDROOM 1	*20	1	1120			480	1	20	RECEPTACLES – DINING	ø12	14
15	ø12	BEDROOM 2, SMOKE DETECTORS	*20	1	1120			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS & EXHAUST – BA3H 1	20	1	150			1120	1	20	RECEPTACLES – LIVING RM., DESK, ENTRY, DINING RM.	ø12	18
19	ø12	LIGHTS & EXHAUST – BA3H 2	20	1	150			160	1	20	RECEPTACLE – BA3H 1	ø12	20
21	ø12	LIGHTS – STORAGE, PATIO MECH., DINING, ENTRY, LIVING RM.	20	1	600			160	1	20	RECEPTACLE – BA3H 2	ø12	22
23	ø0	DRYER	30	2	3500			1080	1	20	RECEPTACLES – UTILITY, WASHER	ø12	24
25					3500			–	1	20	SPARE	–	26
27	–	SPARE	20	1	–			–	1	20	SPARE	–	28
29	–	SPARE	20	1	–			–	1	20	SPARE	–	30

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,570
A=23,565 B=24,105

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: F
LOCATION: BLDG UNIT 3A – UTILITY
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 3 TON	40	2	2400			5400	2	50	RANGE	ø0	2
3					2400			5400					4
5	ø0	AHU 7.5 KW	40	2	2750			1000	1	20	MICROWAVE / VENTHOOD	ø12	6
7					2750			1680	1	20	REFRIGERATOR, DESK RECEPTICLE	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			1500	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	BEDROOM 1	*20	1	1120			480	1	20	RECEPTICALS – DINING	ø12	14
15	ø12	BEDROOM 2	*20	1	1120			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	BEDROOM 3 & SMOKE DETECTORS	*20	1	1120			1600	1	20	RECEPTACLES – HALL, ENTRY LIVING RM., STORAGE, PATIO	ø12	18
19	ø12	LIGHTS & EXHAUST – BA3H 1	20	1	150			160	1	20	RECEPTACLE – BA3H 1	ø12	20
21	ø12	LIGHTS & EXHAUST – BA3H 2	20	1	150			160	1	20	RECEPTACLE – BA3H 2	ø12	22
23	ø12	LIGHTS – UTILITY, KITCH, DESK HALL, LIVING, PATIO, ENTRY, STORAGE	20	1	600			1000	1	20	RECEPTACLES – UTILITY, WASHER	ø12	24
25	ø0	DRYER	30	2	3500			1000	1	20	MICROWAVE	ø12	26
27					3500			–	1	20	SPARE	–	28
29	–	SPARE	20	1	–			–	1	20	SPARE	–	30

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,570
A=25,830 B=19,740

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: G
LOCATION: BLDG UNIT 2A–HC – BEDROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 3.5 TON	30	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 7.5 KW	40	2	2500			100	1	20	VENTHOOD	ø12	6
7					2500			1480	1	20	REFRIGERATOR	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			1500	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	BEDROOM 1	*20	1	1120			480	1	20	RECEPTACLES – DINING	ø12	14
15	ø12	BEDROOM 2, SMOKE DETECTORS	*20	1	1120			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS & EXHAUST – BA3H 1	20	1	150			1120	1	20	RECEPTACLES – ENTRY, LIVING, HALL	ø12	18
19	ø12	LIGHTS & EXHAUST – BA3H 2	20	1	150			160	1	20	RECEPTACLE – BA3H 1	ø12	20
21	ø12	LIGHTS – STORAGE, HALL LIVING RM., ENTRY, DINING, KITCH.	20	1	600			160	1	20	RECEPTACLE – BA3H 2	ø12	22
23	ø12	WASHER	20	1	660			660	2	20	DRYER	ø0	24
25	–	SPARE	20	1	–			2500					26
27	–	SPARE	20	1	–			–	1	20	SPARE	–	28
29	–	SPARE	20	1	–			–	1	20	SPARE	–	30

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=45,010
A=25,410 B=19,600

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: K
LOCATION: LEASING / CLUBHOUSE – 1 BEDROOM
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP COMPRESSOR 2 TON	30	2	1725			5400	2	50	RANGE	ø0	2
3					1725			5400					4
5	ø0	AHU 5 KW	30	2	2500			1000	1	20	MICROWAVE / VENTHOOD	ø12	6
7					2500			1480	1	20	REFRIGERATOR	ø12	8
9	ø0	WATER HEATER	30	2	3600			1600	1	20	RECEPTACLES – COUNTER	ø12	10
11					3600			1000	1	20	GARBAGE DISPOSAL, DISHWASHER	ø12	12
13	ø12	RECEPTACLES & SMOKE DETECTORS – BEDROOM	*20	1	1120			480	1	20	RECEPTACLES – DINING	ø12	14
15	ø12	LIGHTS & EXHAUST – BA3H	20	1	150			1600	1	20	RECEPTACLES – COUNTER	ø12	16
17	ø12	LIGHTS – UTIL., KITCH., DINING, ENTRY, LIVING	20	1	600			160	1	20	RECEPTACLE – BA3H	ø12	18
19	ø12	RECEPTACLES – HALL, LIVING, ENTRY	20	1	1120			2500	2	20	DRYER	ø0	20
21	ø12	WASHER	20	1	660			2500					22
23	–	SPARE	20	1	–			–	1	20	SPARE	–	24

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=43,150
A=21,575 B=21,575

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: HP
LOCATION: NEAR SERVICE EQUIPMENT
FEEDER SOURCE: ENTERGY

NEMA 3R ENCLOSURE

VOLTAGE: 120/240V, 60A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø12	LIGHTING – BREEZEWAY	20	1	320			660	1	20	MAINTENANCE RECEPTACLES	ø12	2
3	ø12	EXTERIOR LIGHTS	20	1	1410			660	1	20	MAINTENANCE RECEPTACLES	ø12	4
5	ø12	LIGHTING – BREEZEWAY	20	1	320			–	1	20	EMERGENCY	ø12	6
7	–	SPARE	20	1	–			–	1	20	SPARE	–	8
9	–	SPARE	20	1	–			–	1	20	SPARE	–	10

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=2,670
A=1,400 B=1,270

GROUND BUS / GROUND WIRE (G)

PANEL: EP
LOCATION: LEASING / CLUBHOUSE MAINTENANCE RM. 24
FEEDER SOURCE: ENTERGY

120/240V, 200A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø0	HP #3 6 TON	50	2	4025			4800	2	60	HP #5 6 TON	ø0	2
3					4025			4800					4
5	ø0	AHU #3 7.5 KW	40	2	2750			5000	2	60	AHU #5 10 KW	ø0	6
7					2750			5000					8
9	ø0	HP #4 6 TON	60	2	4800			5000	2	60	AHU #6 10 KW	ø0	10
11					4800			5000					12
13	ø0	AHU #4 10 KW	60	2	5000			3600	2	30	WATER HEATER	ø0	14
15					5000			3600					16
17	ø0	AHU #6 10 KW	60	2	5000			1600	1	20	RECEPTACLES – COUNTER	ø12	18
19					5000			1600	1	20	RECEPTACLES – COUNTER	ø12	20
21	ø12	MICROWAVE	20	1	1000			1800	1	20	DISHWASHER	ø12	22
23	ø12	REFRIGERATOR	20	1	1480			160	1	20	GFI RECPT. – 1st FL MEN'S, EXTERIOR	ø12	24
25	ø12	GARBAGE DISPOSAL	20	1	575			160	1	20	GFI RECPT. – 1st FL WOMEN'S, EXTERIOR	ø12	26
27	ø12	RECEPTACLES – MAINT., HALL	20	1	1120			1120	1	20	RECEPTACLES – EXERCISE RM.	ø12	28
29	ø12	RECEPTACLES – REC. ROOM	20	1	960			1120	1	20	RECEPTACLES – EXERCISE RM.	ø12	30
31	ø12	RECEPTACLES – MEDIA RM., HALL	20	1	1120			960	1	20	RECEPTACLES – EXERCISE RM., HALL	ø12	32
33	ø12	RECEPTACLES – RECEPT., ASST. MANR., HALL	20	1	1120			800	1	20	RECEPTACLES – LEASE AREA	ø12	34
35	ø12	RECEPTACLES – RECEPT., LEASE AREA	20	1	800			1120	1	20	RECEPTACLES – RECEPT. DESK, COPY / FILE ROOM	ø12	36
37	ø12	RECEPTACLES – MANAGER	20	1	880			1120	1	20	SMOKE DETECTORS	ø12	38
39	ø12	VENDING MACHINES	20	1	1200			–	1	20	SPARE	–	40
41	–	SPARE	–	1	–			–	1	20	SPARE	–	42

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=63,140
A=31,280 B=31,860

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

PANEL: EL
LOCATION: LEASING / CLUBHOUSE MAINTENANCE RM. 24
FEEDER SOURCE: ENTERGY

VOLTAGE: 120/240V, 150A 1ø, 3W, MLO
SURFACE MOUNTED W/EQUIPMENT GND BAR

CKT. NO.	BREAKER SIZE	LOAD DESCRIPTION LOCATION	BREAKER AMP	BREAKER POLE	LOAD (VA)	A	B	LOAD (VA)	BREAKER POLE	BREAKER AMP	LOAD DESCRIPTION LOCATION	BREAKER SIZE	CKT. NO.
1	ø12	EXTERIOR LIGHTS – 1st FLOOR	20	1	1725			5400	1	20	LIGHTS – 1st FLOOR REC. RM.	ø12	2
3	ø12	EXTERIOR LIGHTS – 1st FLOOR	20	1	1725			5400	1	20	LIGHTS – 1st FLOOR REC. RM.	ø12	4
5	ø12	EXTERIOR LIGHTS – 1st FLOOR	20	1	2500			100	1	20	LIGHTS – 1st FLOOR REC.,BIL. KITCHEN	ø12	6
7	ø12	EXTERIOR LIGHTS – 1st FLOOR	20	1	2500			1480	1	20	LIGHTS – 1st FLOOR HALL, MAINT., MEDIA	ø12	8
9	ø12	EXTERIOR LIGHTS – 1st FLOOR	20	1	2600			1600	1	20	LIGHTS – 1st FLOOR RECEPTION	ø12	10
11	ø12	EXTERIOR LIGHTS – 2nd FLOOR	20	1	2600			575	1	20	LIGHTS – 1st FLOOR LEASE AREA	ø12	12
13	ø12	EXTERIOR LIGHTS – 2nd FLOOR	*20	1	1120			1600	1	20	LIGHTS – 1st FLOOR LEASE AREA	ø12	14
15	ø12	EXTERIOR LIGHTS – 2nd FLOOR	*20	1	1120			1600	1	20	LIGHTS – 1st FLOOR COPY, MANR., AST. MANR., REST ROOMS	ø12	16
17	ø12	EMERGENCY LIGHTS 1st FLOOR	20	1	150			1150	1	20	LIGHTS – 1st FLOOR EXERCISE ROOM	ø12	18
19	ø12	EMERGENCY LIGHTS 1st & 2nd FLOORS	20	1	150			160	1	20	LIGHTS – 1st FLOOR EXERCISE RM., VEND.	ø12	20
21	ø12	LIGHTS – STAIR, 2nd FLOOR HALL & CLG.	20	1	600			160	1	20	SPARE	ø12	22
23	–	SPARE	20	1	–			1120	1	20	SPARE	ø12	24

SOLID NEUTRAL / NEUTRAL WIRE (N)

TOTAL CONNECTED LOAD (VA)=38,400
A=18,875 B=19,525

GROUND BUS / GROUND WIRE (G)

* CIRCUIT BREAKERS DENOTED WITH AN ASTERISK SHALL BE ARC-FAULT INTERRUPTING TYPE CIRCUIT BREAKERS

ELECTRICAL PANELS
SCALE: NO SCALE

DAMMON
ENGINEERING, INC.

CHIEF ENGINEER
EMMETT
DAMMON, P.E.

CHIEF ARCHITECT
ROBERT
WILTSE

1095 FLORIDA AVENUE
SLIDELL, LA. 70458
OFFICE: 985-649-5832
FAX: 985-641-5950

WEBSITE:
WWW.DAMMONENGINEERING.COM

EMAIL:
DAMMONENG@BELLSOUTH.NET

ARCHITECTURE

ENGINEERING

STUDIES

PLANNING

INVESTIGATION

EXPERT WITNESS

NEW
APARTMENT
COMPLEX

CROSSWINDS
APARTMENTS
HAMMOND, LA

ELECTRICAL
PANELS

REV:

SCALE: AS NOTED

JOB#: 208112.13

DATE: 12-16-09

SHEET

E-2

OF