

ELECTRICAL ROUGH-IN SCHEDULE

THE SAENGER
THEATRE RENEWAL
PROJECT
142 North Rampart Street
New Orleans, LA

Client
Saenger Theatre Redevelopment Company
200 West Loop South, Suite
1040 Houston TX 77027

Architect
MARTINEZ+JOHNSON
ARCHITECTURE

1412 Eye St. NW
Washington, DC 20005
202.333.4480

Structural Engineer
Shawn J. Franke, P.E.
549 Helmer Road San
Antonio TX 78232
210.979.7900


Theatre Consultant
Schuler Shook
123 Third Street North #210
Minneapolis, MN 55401
612.338.9988

Acoustical Engineer
Akustiks
93 North Main Street South
Norwalk, CT 06854
202.299.1904

MEP Engineer
JBA Consulting Engineers, Inc.
3525 N. Causeway Blvd., Suite
500 Metairie, LA 70002
504.830.0139

Civil Engineer
Linfield, Hunter, & Junius, Inc.
3608 18th Street Suite 200
Metairie, LA 70002
504.835.5300

Architectural Historian
EHT Traceries, Inc.
1121 Fifth Street NW
Washington, DC 20001
202.393.1199



Next Step Design
FOODSERVICE CONSULTANTS
1116 West Street, Suite C
Annapolis, MD 21401
410.263.1200

THESE DRAWINGS, SPECIFICATIONS AND OTHER DOCUMENTS (COLLECTIVELY, "THE DOCUMENTS") INCLUDING WITHOUT LIMITATION ELECTRONIC VERSIONS THEREOF AND THE IDEAS, DESIGNS AND ARRANGEMENTS REPRESENTED THEREBY ARE AND SHALL REMAIN THE PROPERTY OF MARTINEZ & JOHNSON ARCHITECTURE, P.C. AS DEFINED BY APPLICABLE CONTRACTUAL AGREEMENTS ("THE AGREEMENTS") AND AS PROTECTED BY THE COPYRIGHT STATUTES OF THE UNITED STATES. USE OF THE DOCUMENTS SHALL BE STRICTLY LIMITED TO THE PROJECT FOR WHICH THEY WERE PREPARED AND DEVELOPED ("THE PROJECT") PER THE TERMS OF THE AGREEMENTS. NO PART OF THE DOCUMENTS SHALL BE COPIED, DISCLOSED TO OTHERS, OR USED IN CONNECTION WITH ANY OTHER WORK OR PROJECT, OR BY ANY OTHER PERSONS FOR ANY PURPOSES, OTHER THAN THE COMPLETION OF THE PROJECT, WITHOUT THE SPECIFIC WRITTEN AUTHORIZATION OF MARTINEZ & JOHNSON ARCHITECTURE, P.C. THE DOWNLOADING, OPENING, OR VIEWING OF ELECTRONIC VERSIONS OF THE DOCUMENTS OR VISUAL CONTACT WITH ANY PRINTED FORM THEREOF SHALL CONSTITUTE CONCLUSIVE EVIDENCE OF ACCEPTANCE OF THESE RESTRICTIONS.

7502

DATE:	No.:	ISSUE:
02.19.10	1	PERMIT SET
04.02.10	2	GMP CONTRACT SET
11.11.10	-	CONTRACT SET

DATE:	No.:	REVISION:

SHEET TITLE:
**FOODSERVICE -
ELECTRICAL
ROUGH-IN SCHEDULE**

FS-E5.1

KEY	ITEM	DESCRIPTION	Volt/ Ph	HP/ KW	Amp/ Conn	Height
E 303		SPARE NUMBER				
E 304		SPARE NUMBER				
E 305		CONVENIENCE OUTLET Two (2) rough-in locations required. *Circuit size indicated.	120 1		20* 2DR	39" AFF
E 306	308	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	39" AFF
E 307	309	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	39" AFF
E 308		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 309		CONVENIENCE OUTLET Two (2) rough-in locations required. *Circuit size indicated.	120 1		20* 2DR	39" AFF
E 310		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 311	320	LIQUOR GUN *Circuit size indicated.	120 1		*20 DR	16" AFF
E 312	317	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 313		SPARE NUMBER				
E 314		SPARE NUMBER				
E 315	318	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 316	325	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 317	328	BOTTLE COOLER *Circuit size indicated.	120 1	1/5	15.0 SR	16" AFF
E 318	331	LIQUOR GUN *Circuit size indicated.	120 1		*20 DR	16" AFF
E 319	335	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 320		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 321	337	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	16" AFF
E 322	339	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	16" AFF
E 323		SPARE NUMBER				
E 324		SPARE NUMBER				
E 325		CONVENIENCE OUTLET Two (2) rough-in locations required. *Circuit size indicated.	120 1		20* 2DR	39" AFF
E 326	350	LIQUOR GUN *Circuit size indicated.	120 1		*20 DR	16" AFF
E 327		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 328	347	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 329	348	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 330	352	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 331	358	BOTTLE COOLER *Circuit size indicated.	120 1	1/5	15.0 SR	16" AFF
E 332	361	LIQUOR GUN *Circuit size indicated.	120 1		*20 DR	16" AFF
E 333		SPARE NUMBER				

KEY	ITEM	DESCRIPTION	Volt/ Ph	HP/ KW	Amp/ Conn	Height
E 334		SPARE NUMBER				
E 335	365	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 336		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 337	368	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 338	369	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 339		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 340	380	LIQUOR GUN *Circuit size indicated.	120 1		*20 DR	16" AFF
E 341	377	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 342	378	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit.	120 1		20* SR	24" AFF
E 343		SPARE NUMBER				
E 344		SPARE NUMBER				
E 345	382	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 346	386	BOTTLE COOLER Dedicated 15 amp circuit	120 1	1/5	6.1 SR	16" AFF
E 347		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 348		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	39" AFF
E 349		CONVENIENCE OUTLET Quad receptacle. Two rough-in locations required. *Circuit size indicated.	120 1		20* 2DR	16" AFF
E 350	396	ICE MAKER, CUBE-STYLE 20.0 amp max. fuse size. Electrician to provide Cord & Plug.	120/208 1		8.2 SR	68" AFF
E 351		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	16" AFF
E 352	402	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 353		SPARE NUMBER				
E 354		SPARE NUMBER				
E 355		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 356	415	SODA GUN & CARBONATOR *Circuit size indicated.	120 1		*20 DR	16" AFF
E 357		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 358	422	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit. Electrician to verify grommet location w/ millwork contractor.	120 1		20* SR	24" AFF
E 359	421	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit. Electrician to verify grommet location w/ millwork contractor.	120 1		20* SR	24" AFF
E 360	431	DISHWASHER, UNDERCOUNTER *Circuit size indicated.	208 3	3/4 8.0	25.7 SR	16" AFF
E 361	420	BACKBAR REFRIGERATOR Dedicated 15 amp circuit required.	115 1	1/3	10.1 SR	12" AFF
E 362		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 363		SPARE NUMBER				
E 364		SPARE NUMBER				
E 365	418	POS - CASH REGISTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit. Electrician to verify grommet location w/ millwork contractor.	120 1		20* SR	24" AFF

KEY	ITEM	DESCRIPTION	Volt/ Ph	HP/ KW	Amp/ Conn	Height
E 366	419	POS - PRINTER (VERIFY) Owner supplied item. *Circuit size indicated. Provide on separate circuit w/ isolated ground & COM conduit. Electrician to verify grommet location w/ millwork contractor.	120 1		20* SR	24" AFF
E 367		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 368		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 369	435	REFRIGERATOR, REACH-IN Supplied with Cord & Nema-5-15P Plug.	115 1	1/3	7.0 SR	86" AFF
E 370	432	HEATED CABINET Provided w/ NEMA 6-15P plug.	208 1	2.0	9.6 SR	74" AFF
E 501		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	16" AFF
E 502	505	ICE MAKER, CUBE-STYLE *Minimum 20.0 Amp circuit required. Electrician to interconnect service to Remote Condenser (Item #504.2). Electrician to provide Cord & Plug.	120/208 1		9.5* SR	84" AFF
E 503	504	ICE MAKER, CUBE-STYLE *Minimum 20.0 Amp circuit required. Electrician to interconnect service to Remote Condenser (Item #504.2). Electrician to provide Cord & Plug.	120/208 1		9.5* SR	84" AFF
E 504		SPARE NUMBER				
E 505		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	16" AFF
E 506	511	BOOSTER HEATER, ELECTRIC 90 amp fuse size required.	480 3	57.0	68.6 JB	12" AFF
E 507	512	DISHWASHER, CONVEYOR TYPE Electrician to wire table limit switch at end of Clean Dish Table (BTC from Controls).	480 3	2-1/4 10.0	60 JB	78" AFF
E 508	515	GARBAGE DISPOSER Electrician to BTC thru manual reverse switch.	208 3	2.0	3.3 JB	24" AFF
E 509		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 510		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF
E 511	521	ICE TEA BREWER (VERIFY) Vendor provided item. Electrician to provide cord & plug.	120 1		20.0 SR	54" AFF
E 512	522	COFFEE BREWER *Circuit size indicated.	120/208 1	4.6	22.4 SR	54" AFF
E 513		SPARE NUMBER				
E 514		SPARE NUMBER				
E 515	525	REFRIGERATOR, REACH-IN Supplied with Cord & Nema-5-15P Plug.	115 1	1/3	7.0 SR	86" AFF
E 516		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	16" AFF
E 517		CONVENIENCE OUTLET Four (4) rough-in locations required. *Circuit size indicated.	120 1		20* 4DR	16" AFF
E 518	551	GARBAGE DISPOSER Electrician to BTC thru manual reverse switch.	208 3	2.0	3.3 JB	24" AFF
E 519		SPARE NUMBER				
E 520	546	HOLDING CABINET Provided w/ NEMA 6-15P plug.	208 1	1.5	7.2 SR	74" AFF
E 521	545	HOLDING CABINET Provided w/ NEMA 6-15P plug.	208 1	1.5	7.2 SR	74" AFF
E 522	542	HOLDING CABINET Provided w/ NEMA 6-15P plug.	208 1	1.5	7.2 SR	74" AFF
E 523		SPARE NUMBER				
E 524		SPARE NUMBER				
E 525	558	INDUCTION RANGE, ELECTRIC Three (3) rough-in locations required.	208 1	2.5 ca.	12.0 ca. 3SR	48" AFF
E 526		CONVENIENCE OUTLET *Circuit size indicated.	120 1		20* DR	48" AFF

FOODSERVICE - ELECTRICAL ROUGH-IN SCHEDULE

NONE

1